

VIDEO WALL CONTROLLER

SherPlayer SSI-VWC4U-MURA



Features

- Up to 28 inputs/outputs of Full HD video in a single box
- Convenient 4U chassis easily converts to a tower
- Includes MuraControl for Windows
- Up to 12 4K Outputs
- Great solution for video walls, control rooms, and sports centers

Specifications

Chassis	4U Rackmount or Stand-Alone Installation	
Processor	Intel® Core™ i7-5930K 6 Core 3.5GHz 15MB Cache	
Operating System	Windows 7 Pro 64-Bit	
Video Inputs/Outputs	Up to 28 inputs and 28 outputs	
Hard Drive	1TB 7200RPM HDD (Optional Raid)	
Memory	32GB DDR4 2133MHz Memory	
Dimensions	546 x 430 x 176 (mm), 21.5" x 16.9" x 6.9"	
Rear I/O Ports	2 x eSATA 2 x LAN (RJ45) port(s) 10 x USB 3.0 (blue) 8 x Audio jack(s) 1 x Optical S/PDIF out 1 x USB BIOS Flashback Button(s) 1 x Q-Code Logger button	
Power Supply	750w 80PLUS Platinum (Optional Redundant PSU Available)	
Warranty	3 Year Depot Warranty (Install and Training options available)	
LAN	Intel® I210-AT, 1 x Gigabit LAN Controller(s) Intel® I218LM, 1 x Gigabit LAN, Dual interconnect between the Integrated Media Access Controller (MAC) and Physical Layer (PHY)	
Optical Drive	24x DVD RW	
Software	MuraControl for Windows is included. Its a feature rich, single-license software that enables precise remote or local control of your video wall.	
Recommended Cards	Mix and Match MPX Cards For Your Solution <ul style="list-style-type: none"> • MURA-MPX40HF - 4 Output / 0 Input Solutions • MURA-MPX42HF - 4 Output / 2 Input Solutions • MURA-MPX44HF - 4 Output / 4 Input Solutions • MURA-MPXV8F - 8 Analog Input Only • MURA-MPXV16F - 16 Analog Input Only • MURA-MPXSDI - 2 DVI Output / 2 SDI Input 	IPX and C Series <ul style="list-style-type: none"> • MURA-IPX-I4DF 4K Capture and IP Decode board • MURA-IPX-I4EF 4K Capture and IP Encode/Decode board • C680-E2GBF Six 4K Output
Display Console	Add a P Series card to have a display console separate from the video wall.	

